Document downloaded from:

http://hdl.handle.net/10251/176076

This paper must be cited as:

Floris, I.; Madrigal-Madrigal, J.; Sales Maicas, S.; Adam, JM.; Calderón García, PA. (2020). Experimental study of the influence of FBG length on optical shape sensor performance. Optics and Lasers in Engineering. 126:1-7. https://doi.org/10.1016/j.optlaseng.2019.105878



The final publication is available at

https://doi.org/10.1016/j.optlaseng.2019.105878

Copyright Elsevier

Additional Information

Experimental study of the influence of FBG length on Optical Shape Sensor performance

Ignazio Floris ^{a,b}, Javier Madrigal ^a, Salvador Sales ^a, Jose M. Adam ^{b*}, Pedro A. Calderón ^b

^aITEAM, Universitat Politècnica de València, Camino de Vera s/n, Valencia, 46022, Spain ^bICITECH, Universitat Politècnica de València, Camino de Vera s/n, Valencia, 46022, Spain

Abstract

This paper compares the performance of optical Multicore Fibres (MCFs) with inscribed Fibre Bragg Gratings (FBGs) used as curvature and shape sensors in relation to strain sensor length. Two fibre optic shape sensors, consisting of FBGs written in standard optical multicore fibre (diameter 124.5 µm), were assembled in the Institute for Telecommunications and Multimedia Applications (iTEAM) of the *Universitat Politècnica de València*. The optical sensors were then positioned on an aluminium mould and quasidistributed curvature and shape sensing were performed to compare the accuracy of the arrays. It was found that the MCF shape sensor performance strongly depended on FBG length and that sensors based on long FBGs were significantly more accurate, showing that long FBGs can considerably improve shape sensor accuracy at equal grating densities and achieve substantially better performance. This is a great advantage when wavelength division multiplexing is used, when only a limited number of usable FBGs can be applied. These new results, applicable to both multiple single-core optical fibres and multicore optical fibres with embedded quasi-distributed strain sensors, show the connection between strain sensor length and accuracy, hardly taken into account in previous studies, and lay the foundation for the design of new long-FBG-based

 Keywords: Optical Fiber Sensor; Distributed sensing; Multicore Optical Fibre; Bending/Curvature Sensor; Optical Shape Sensing.

1. Introduction

shape sensors.

Fibre Bragg Gratings (FBGs) have been extensively used as strain and temperature sensors [1,2], since they were first proposed in the late 1980s [3]. FBG sensors have many engineering applications [4–9] thanks to their advantages over electric sensors, including: intrinsic safety, multiplexing capabilities, immunity to electromagnetic interference (EMI), resistance to radiation, chemicals and harsh temperatures, light weight and compactness.

Fibre Optic Shape Sensors (FOSS) consist of multiple-core optical cables (a central core and several external cores equally spaced from the sensor axis) with embedded quasi-distributed strain sensors such as FBGs and allow the calculation of local bending (curvature and bending direction) along the fibre based on the strain detected in each core. The 3D fibre shape can thus be reconstructed from the bending parameters [10]. In this way, a cost-effective, compact and monolithic fibre-optic array can be obtained for continuous high-precision 3D shape sensing.

^{*} Corresponding author.

Curvature and shape sensing by Multicore Fibres (MCFs) are attractive for a number of medical, industrial, civil and defence related applications [11,12]. Villatoro et al. reported on an ultrasensitive bending sensor based on a MCF to monitor the verticality of towers, bridge piles, and buildings [13]. A two-axis temperature-insensitive accelerometer was developed from a multicore FBG bending sensor [14]. Westbrook et al. developed a continuous MCF-based shape sensor for distributed sensing applications [15]. Larkin and Shafer filed a patent in 2011 for a completely robotic surgical system through optical fibre bending sensor based on FBGs [16]. Moon et al. developed an MCF-based ultrathin shape sensor for minimally invasive surgery [17]. MacPherson et al. first demonstrated a multicore fibre displacement sensor with inscribed FBGs for tunnel monitoring [18]. A curvature and shape MCF sensor for continuum robotics was manufactured in 2018 using Draw Tower Gratings (DTG®s) [19]. Khan et al. reported on the development of a shape sensor for flexible medical instruments based on a multicore optical fibre with Bragg gratings [20].

This paper reports on an experimental study carried out to identify the influence of FBG length on optical shape sensor performance. Two optical shape sensor arrays were assembled in the Institute of Telecommunications and Multimedia Applications (iTEAM) of the *Universitat Politècnica de València* (UPV) by writing 1.5 and 8.0 mm-long Bragg gratings in a standard non-twisted homogeneous 7-core fibre (diameter 124.5 µm) [21]. The sensors were then placed in an aluminium mould and tested by an Optical Spectrum Analyser (OSA) based on Wavelength Division Multiplexing (WDM) analysis.

It was found that at the same FBG density the long-FBG-based shape sensor achieved remarkably better accuracy in the entire shape reconstruction process, including strain sensing, curvature calculation and shape integration. Long FBGs can thus notably enhance optical shape sensing accuracy. They are especially useful when FBG density cannot be increased to improve shape reconstruction efficiency, as in WDM analysis, one of the most widely used techniques thanks to their low-cost and high-speed data acquisition, and when the number of usable gratings is limited. However, substituting long FBGs for the short variant can also give better shape reconstruction accuracy in Optical Frequency Domain Reflectometry (OFDR), which can interrogate thousands of gratings [22] with an equal number of strain sensors. Although only multicore fibre sensors were considered, the outcomes are also applicable to optical shape sensors, needles and inclinometers composed of multiple mono-core optical fibres with embedded strain-sensors, which have the same geometry as multicore fibres, but greater core spacing to achieve higher precision [23–27].

This paper first demonstrates the relationship between MCF-based shape sensor accuracy and FBG length and then describes the remarkable benefits of strong gratings and hence lays the foundations for the design of more accurate shape sensors.

2. Sensing system and principles

2.1. Shape sensors fabrication

The shape sensors were assembled in the Institute of Telecommunications and Multimedia
Applications (iTEAM) of the Universitat Politècnica de València (UPV) by inscribing four FBGs
with a length of 1.5 mm and 8.0 mm (equally spaced along a length of 45mm) in a commercial
seven-core MCF from Fibercore Ltd. [21]. The fibre had a cladding diameter of 124.5µm and
seven cores with doubly symmetric configuration (see Fig. 1): one central core and six external

cores equidistant from the fibre axis (core spacing 35 µm) and 60° of angular spacing. Each core had a mode field diameter of 6.4 µm and a numerical aperture of 0.2.



Fig. 1. Seven- core MCF cross section [21]

In order to enhance photosensitivity, the fibre optic was hydrogen loaded for two weeks at ambient temperature and a pressure of 20 bars. The phase-mask method [1] was used to inscribe the fibre Bragg gratings by a 244 nm CW frequency-doubled argon-ion laser with 60 mW output power. The spectrum of the central core of both sensors is shown in Fig. 2.






Fig. 2. Spectrum comparison of the two sensors with long and short FBGs.

2.2. Shape reconstruction

Optical Fibre Sensors (OFS) with multiple cores and embedded strain sensors have shape reconstruction capabilities. Kirchhoff's rod hypotheses (which state that the cross sections remain plane and normal to the centreline and that the centreline is inextensible [28]) are applicable to the present study (negligible shear deformation) and can be used to define the relationship between the deformed fibre frame and 3D curve frame along the sensor length, when the fibre optic cable is bounded at one extremity in the absence of friction [29].

Under the assumptions of the elastic rod theory, the strain varies linearly along each section when the fibre is bent and external torsion/twisting is avoided (there is no local twisting). This torsion/twisting should not be confused with the geometric torsion τ . If twisting cannot be prevented, the torsional strain can be calculated by comparing the strain sensed by the external cores and the central core, where the strain component is zero, and the bending strain can be considered separately [30].

In the light of the above, the bending strain function, $\varepsilon(x,y)$, which describes the strain variation

due to bending along the section (strain surface), is a plane. The equation of this plane (see Eq.1)

- can be determined from the coordinates of the cores (after defining a local Cartesian Coordinate
- System (x,y) centred on the mid-section) and the strains measured by at least three non-aligned
- 111 cores, although additional cores can be used to obtain higher precision. Moreover, temperature
- compensation is not necessary, since, thanks to the small core spacing, temperature variations
- affect all the cores equally (there are no temperature gradients inside the section).
- The coefficients of the plane can be equated by minimising the Sum of Squared Errors (SSE),
- as shown in the following Equations [31]:

116
$$\varepsilon(x, y) = a + bx + cy \tag{1}$$

117
$$SSE(a, b, c) = \sum_{i=1}^{n} (\varepsilon_i - a - bx_i - cy_i)^2$$
 (2)

118
$$\nabla SSE(a,b,c) = 0 \tag{3}$$

$$\begin{cases}
\frac{\partial SSE(a,b,c)}{\partial a} = 0 \to na + b \sum_{i=1}^{n} x_i + c \sum_{i=1}^{n} y_i = \sum_{i=1}^{n} \varepsilon_i \\
\frac{\partial SSE(a,b,c)}{\partial b} = 0 \to a \sum_{i=1}^{n} x_i + b \sum_{i=1}^{n} x_i^2 + c \sum_{i=1}^{n} x_i y_i = \sum_{i=1}^{n} x_i \varepsilon_i \\
\frac{\partial SSE(a,b,c)}{\partial c} = 0 \to a \sum_{i=1}^{n} y_i + b \sum_{i=1}^{n} x_i y_i + c \sum_{i=1}^{n} y_i^2 = \sum_{i=1}^{n} y_i \varepsilon_i
\end{cases} \tag{4}$$

- where a, b, and c are the coefficients of the bending strain plane equation, n is the number of
- 121 cores, x_i , y_i and ε_i are the coordinates and the strain of the *ith* core. 122
- The approach described above is valid for a generic MCF section with n cores. In the case of a
- seven-core fibre, thanks to the doubly symmetry of the section, the system of equations becomes
- 125 diagonal:

126
$$\begin{cases} na + 0 + 0 = \sum_{i=1}^{n} \varepsilon_{i} \\ 0 + b \sum_{i=1}^{n} x_{i}^{2} + 0 = \sum_{i=1}^{n} x_{i} \varepsilon_{i} \\ 0 + 0 + c \sum_{i=1}^{n} y_{i}^{2} = \sum_{i=1}^{n} y_{i} \varepsilon_{i} \end{cases}$$
 (5)

- The coefficients of bending strain plane, a, b, and c represent the average longitudinal strain,
- 128 ε_{long} , and the two components of curvature, κ_x and κ_y , respectively; the latter two being the partial
- derivatives of $\varepsilon(x,y)$ with respect to x and y. Therefore, the equations become:

130
$$\begin{cases} \varepsilon_{long} = \sum_{i=1}^{n} \varepsilon_i / n \\ \kappa_x = \sum_{i=1}^{n} x_i \varepsilon_i / \sum_{i=1}^{n} x_i^2 \\ \kappa_y = \sum_{i=1}^{n} y_i \varepsilon_i / \sum_{i=1}^{n} y_i^2 \end{cases}$$
 (6)

- Once known the coefficients of bending strain function, the bending direction angle, α , and the
- magnitude of the vector curvature, $|\kappa|$, can be also determined, as shown in Fig. 3, using the
- 133 following equations:

$$|\kappa| = \sqrt{\kappa_x^2 + \kappa_y^2} \tag{7}$$

135
$$\alpha = \tan^{-1}(\kappa_x/\kappa_y) \tag{8}$$




Fig. 3. Strain distribution due to bending of a seven-core fibre

It is worth noting that the central core does not contribute anything to the bending direction angle and curvature calculations, and thus neither to shape reconstruction, even though it can be used to sense twisting.

When the curvature and bending direction angle values are known in several sections, the function of curvature $\kappa(s)$ and torsion $\tau(s)$ along the fibre can be calculated by interpolation or curve fitting [10,32]. Once these functions and the boundary conditions are known, which are the position r_0 and the Frenet frame T_0 , N_0 , B_0 of the starting point, the shape can be reconstructed through numerical integration of the Frenet-Serret formulas [10], which can be written as:

$$\begin{bmatrix} \mathbf{T}' \\ \mathbf{N}' \\ \mathbf{B}' \end{bmatrix} = \begin{bmatrix} 0 & \kappa & 0 \\ -\kappa & 0 & \tau \\ 0 & -\tau & 0 \end{bmatrix} \begin{bmatrix} \mathbf{T} \\ \mathbf{N} \\ \mathbf{B} \end{bmatrix}$$
(9)

where T, N and B are respectively tangent, normal and binormal vectors.

The flowchart of the whole shape reconstruction process is shown in Fig. 4.




Fig. 4. Flowchart of shape reconstruction process.

The torsion function was not calculated in this study, since the fibre was neither spun nor fastened to the mould, and so, as it was impossible to calculate either torsional strain or avoid fibre twisting, 2D shape sensing was used. In this case, the Frenet-Serret formulas become:

160
$$\begin{bmatrix} \mathbf{T}' \\ \mathbf{N}' \end{bmatrix} = \begin{bmatrix} 0 & \kappa \\ -\kappa & 0 \end{bmatrix} \begin{bmatrix} \mathbf{T} \\ \mathbf{N} \end{bmatrix}$$
 (10)

2.3. Experimental setup

In order to test sensor performance, an experimental setup was designed to ensure accurate readings. An aluminium mould was made on a high-precision computer numerical controlled (CNC) machine with a maximum positioning error of a few tens of micrometers to ensure the marginal influence of fibre positioning errors on shape reconstruction accuracy. The mould (see Fig. 5) consisted of a plate with five engraved semicircles with radii of 55, 50, 45, 40 and 35 mm, for Tests1 to 5, respectively.




Fig. 5. Shape-sensing mould

The fibres were placed around each of the semi-circles on the mould, from the lowest to the highest curvature, and stretched along the semicircles using two multi-axis stages for nanopositioning, interrogated by a Static Optical Sensing Interrogator (sm125) combined with a Channel Multiplexer (sm041) (Micron Optics). The experimental setup can be seen in Fig. 6.




Fig. 6. Experimental setup

3. Results and discussion

3.1. Strain sensing results

Since the local bending in each instrumented section was calculated from the strain sensed by the cores, the repeatability and precision of the MCF strain sensors were first assessed by tracking

the FBG peaks simultaneously in all seven cores at a constant temperature for two minutes at an acquisition rate of 0.5 Hz. The shift in the FBG wavelength was then converted into strain by dividing the wavelength shift by a gauge factor value equal to 1.2 microstrain/pm, obtained from different tensile tests in accordance with [33].

The measured strain values followed a normal distribution. Their standard deviations (SD) are reported in Table 1:

Table 1. Comparison of the normal strain distribution SDs detected by MCF shape sensors.

Standard Deviation of Strain Measurements [με] - Test 1								
	Core 1	Core 2	Core 3	Core 4	Core 5	Core 6	Core 7	
FBG 1	0.4911	0.6175	0.5673	0.5437	0.5616	0.6042	0.6095	
FBG 2	0.6126	0.6045	0.5823	0.5400	0.4553	0.4629	0.5776	Long
FBG 3	0.4590	0.7009	0.8630	0.6308	0.6439	0.4951	0.5001	FBGs
FBG 4	0.5586	0.6590	0.7115	0.6467	0.5339	0.6587	0.5356	
FBG 1	1.7457	2.0023	1.9268	1.6449	1.6916	2.3905	1.7643	
FBG 2	2.3445	1.8208	1.6640	2.5776	1.6821	2.0045	1.8354	Short
FBG 3	1.9885	1.6443	2.3988	2.5314	3.0691	1.7810	1.3503	FBGs
FBG 4	1.5843	1.5292	2.0616	2.6288	2.2684	2.0137	1.9562	

The strain distribution SDs were mostly homogeneous in all the sections and cores of both sensors and were strongly affected by grating length. In fact, those of the short FBGs were three or four times higher than those detected by the long FBGs.

Strain detection precision depends on the accuracy of the interrogation system, which is related to the resolution of the read-out of the reflected wavelengths, peak tracking technique [34], FBG spectrum and the noise signal.

3.2. Curvature sensing results

Curvature was calculated from the bending strain, which is the difference between the strain measured in the straight and bent sensors. To calculate the bending strain, the FBG wavelength peaks were initially detected in the straight sensors and then the peaks shifts were tracked in the curved fibres. The wavelength peak shifts were converted into strain by dividing them by the gauge factor, while the curvature was calculated from Eqs. 6 and 7.

Although the peak shifts are influenced by the longitudinal strain due to axial loading and temperature variation, no compensation was necessary since the longitudinal strain affects all the cores equally and therefore has no influence on the slope of the bending strain plane, on which the curvature depends.

Once again, the results of the long-FBG-based MCF are considerably better. The sources of errors in the case of curvature sensing are diverse and include the resolution of the interrogation system and inaccuracy in the geometry of the sensor and in the sensor positioning [31,35,36].

Table 2 lists the curvature detected by both sensors in the five tests.

Table 2. Comparison of curvature values detected by two MCF shape sensors.

	Test 1	Test 2	Test 3	Test 4	Test 5		
Curvature [1/m]	18.1818	20.0000	22.2222	25.0000	28.5714		
Section 1	18.3154	19.7832	22.3003	24.7801	28.3600		
Section 2	17.9226	20.0031	21.9657	25.1781	28.3339		
Section 3	18.5390	19.8496	22.7328	25.3513	28.4611	Long FBGs	
Section 4	17.8365	20.0638	22.3428	24.9200	28.5443		
Average Value	18.1534	19.9249	22.3354	25.0574	28.4248		
Average Error	-0.0284	-0.0751	0.1132	0.0574	-0.1466		
St. Deviation	0.2867	0.1131	0.2720	0.2217	0.0838		
Section 1	17.8974	19.6786	21.5104	25.4391	28.6197		
Section 2	18.2177	19.8971	21.9127	24.5911	28.6836		
Section 3	18.0101	19.6753	22.5028	25.3401	28.6064		
Section 4	19.1247	21.2615	23.7737	25.7340	30.0321	Short FBGs	
Average Value	18.3125	20.1281	22.4249	25.2761	28.9854		
Average Error	0.1306	0.1281	0.2027	0.2761	0.4140		
St. Deviation	0.4828	0.6605	0.8550	0.4212	0.6050		

3.3. Shape sensing results

An algorithm was developed in Mathematica code [37] for the linear interpolation of the curvature function $\kappa(s)$, based on the curvature calculated in the instrumented sections, and to reconstruct the 2D shape of the of MCF arrays through numerical integration of the Frenet-Serret equations (Eq. 10). Fig. 7 shows the shapes of the two fibre optic sensors, which were sensed, while the fibres were stretched along the semicircles on the mould (see Fig. 5), and reconstructed by using the procedure explained in Section 2.2.




Fig. 7. Reconstructed shape of MCF sensors by (a) short FBGs and (b) long FBGs.

In order to evaluate the shape sensors performance, the shape reconstruction errors were determined (considered as the distance between the exact position of the fibres and the reconstructed shape position) (see Fig. 8).




Fig. 8. Shape reconstruction errors of two MCF shape sensor arrays in (a) Test 1; (b) Test 2; (c) Test 3; (d) Test 4; (e)

As in the previous cases, the errors obtained with multicore sensors based on short FBGs are significantly greater, meaning that the strain and curvature sensing errors propagate and affect shape reconstruction, the sources of errors being, in fact, the same discussed in the previous sections. The largest long FBG errors are between 0.05 and 0.20 mm (0.11% and 0.44% of sensor length), while those of the short FBG sensors are several times greater, i.e. between 0.12 and 0.41 mm (0.26% and 0.91% of sensor length) and vary much more widely.

3.4. Discussion

The optical MCF sensor based on long FBGs was shown to be significantly more precise and efficient than the short-FBG-based variant. The main reason for the different performance is due to the capacity of long FBGs to average the local errors of longer sections and to the differences in the sensors' spectra (see Fig. 2). Long FBGs are considerably stronger than short ones and so the peaks are narrower and can be detected more efficiently, as can be seen in Fig. 9.




Fig. 9. Peak comparison of long and short FBGs.

2.72

To sum up, long FBGs can improve the accuracy of fibre optic shape sensors without increasing FBG density per metre. This effect is particularly favourable with the WDM technique, because the number of trackable FBGs is limited and cannot be increased to improve shape reconstruction resolution. In addition, WDM analysis is the only one that reaches high frequency data acquisition.

4. Conclusions

Two optical MCF shape sensors were assembled by inscribing long (8.0mm) and short (1.5mm) FBGs in commercial 7-core fibre. All the necessary steps for shape reconstruction were traced, including strain sensing, curvature calculation and shape integration, and sensor performance was compared at each stage.

The long-FBG-based sensor was found to be considerably more accurate in all conditions than the short, which was attributed to the capacity of the former to average local errors in longer sections and to its stronger and narrower reflection peaks than those of the short ones, which means the wavelength shift of long FBGs is easier to track.

The study first proved that long FBGs can significantly enhance the shape tracking accuracy of optical multicore fibre sensors. When wavelength division multiplexing is employed and the number of usable FBGs is limited and depends on the breadth of the spectral transmission window, long gratings are especially recommended since they can considerably improve precision with the same number of gratings. Nevertheless, even when the FBGs are interrogated by an OFDR, which allows higher grating density by reading up to several thousand gratings, long gratings can still ensure better performance at equal FBG densities. The results obtained apply to both multiple single-core optical fibres and multicore optical fibres with embedded quasidistributed strain sensors, which have the same cross section geometry. In the light of the above, these new results lay the basis for the design of new and more efficient shape sensors.

276 Acknowledgments

- This work was carried out within the ITN-FINESSE framework, funded by the European
- 278 Union's Horizon 2020 Research and Innovation Program under the Marie Sklodowska-Curie
- 279 Action Grant Agreement N° 722509. It was also supported by the Spanish Ministry of Economy
- and Competitiveness within the DIMEN- SION TEC2017-88029-R PROJECT.

References

- 282 [1] Kashyap R. Fiber Bragg Gratings. 2nd Editio. Elsevier; 2009.
- 283 [2] Zhang S, Bae Lee S, Fang X, Sam Choi S. In-fiber grating sensors. Opt Lasers Eng 1999;32:405–18.
 284 doi:10.1016/S0143-8166(99)00052-4.
- Meltz G, Dunphy JR, Glenn WH, Farina JD, Leonberger FJ. Fiber Optic Temperature And Strain Sensors. In: Verga Scheggi AM, editor., 1987, p. 104. doi:10.1117/12.941093.
- 287 [4] Rao Y. Recent progress in applications of in-fibre Bragg grating sensors. Opt Lasers Eng 1999;31:297–324. doi:10.1016/S0143-8166(99)00025-1.
- 289 [5] Campanella C, Cuccovillo A, Campanella C, Yurt A, Passaro V. Fibre Bragg Grating Based Strain Sensors: 290 Review of Technology and Applications. Sensors 2018;18:3115. doi:10.3390/s18093115.
- Ferraro P, De Natale G. On the possible use of optical fiber Bragg gratings as strain sensors for geodynamical monitoring. Opt Lasers Eng 2002;37:115–30. doi:10.1016/S0143-8166(01)00141-5.
- 293 [7] Spirin V., Shlyagin M., Miridonov S., Jiménez FJM, Gutiérrez RML. Fiber Bragg grating sensor for petroleum hydrocarbon leak detection. Opt Lasers Eng 1999;32:497–503. doi:10.1016/S0143-8166(00)00021-X.
- Botsis J, Humbert L, Colpo F, Giaccari P. Embedded fiber Bragg grating sensor for internal strain measurements in polymeric materials. Opt Lasers Eng 2005;43:491–510. doi:10.1016/j.optlaseng.2004.04.009.
- 297 [9] Ma Z, Chen X. Fiber Bragg Gratings Sensors for Aircraft Wing Shape Measurement: Recent Applications and Technical Analysis. Sensors 2018;19:55. doi:10.3390/s19010055.
- 299 [10] Moore JP, Rogge MD. Shape sensing using multi-core fiber optic cable and parametric curve solutions. Opt 300 Express 2012;20:2967. doi:10.1364/OE.20.002967.
- Amanzadeh M, Aminossadati SM, Kizil MS, Rakić AD. Recent developments in fibre optic shape sensing. Meas J Int Meas Confed 2018;128:119–37. doi:10.1016/j.measurement.2018.06.034.
- Wang Q, Liu Y. Review of optical fiber bending/curvature sensor. Meas J Int Meas Confed 2018;130:161–76. doi:10.1016/j.measurement.2018.07.068.
- Villatoro J, Van Newkirk A, Antonio-Lopez E, Zubia J, Schülzgen A, Amezcua-Correa R. Ultrasensitive vector bending sensor based on multicore optical fiber. Opt Lett 2016;41:832–5. doi:10.1364/OL.41.000832.
- Fender A, MacPherson WN, Maier RRJ, Barton JS, George DS, Howden RI, et al. Two-axis accelerometer based on multicore fibre Bragg gratings. IEEE Sens J 2007;8:66190Q-66190Q-4. doi:10.1117/12.738411.
- 309 [15] Westbrook PS, Kremp T, Feder KS, Ko W, Monberg EM, Wu H, et al. Continuous Multicore Optical Fiber Grating Arrays for Distributed Sensing Applications. J Light Technol 2017;35:1248–52. doi:10.1109/JLT.2017.2661680.
- 312 [16] Larkin DQ, Shafer DC. Robotic surgery system including position sensors using fiber bragg gratings.
 313 US7930065B2, 2011.
- Moon H, Jeong J, Kang S, Kim K, Song Y-W, Kim J. Fiber-Bragg-grating-based ultrathin shape sensors displaying single-channel sweeping for minimally invasive surgery. Opt Lasers Eng 2014;59:50–5. doi:10.1016/j.optlaseng.2014.03.005.
- MacPherson WN, Silva-Lopez M, Barton JS, Moore AJ, Jones JDC, Zhao D, et al. Tunnel monitoring using multicore fibre displacement sensor. Meas Sci Technol 2006;17:1180–5. doi:10.1088/0957-0233/17/5/S41.
- Jan VR, Vincent M, Eric L, Bram VH, Christian V, Johan V, et al. Curvature and Shape Sensing for Continuum Robotics using Draw Tower Gratings in Multi Core Fiber. 26th Int. Conf. Opt. Fiber Sensors, Washington, D.C.:

- 321 OSA; 2018, p. ThE70. doi:10.1364/OFS.2018.ThE70.
- Khan F, Denasi A, Barrera D, Madrigal J, Sales S, Misra S. Multi-core Optical Fibers with Bragg Gratings as Shape Sensor for Flexible Medical Instruments. IEEE Sens J 2019;PP:1–1. doi:10.1109/JSEN.2019.2905010.
- 324 [21] https://www.fibercore.com/product/multicore-fiber n.d.
- Childers BA, Froggatt ME, Allison SG, Moore, Sr. TC, Hare DA, Batten CF, et al. Use of 3000 Bragg grating
 strain sensors distributed on four eight-meter optical. In: McGowan A-MR, editor., 2001, p. 133–42.
 doi:10.1117/12.429650.
- Lenke P, Wendt M, Krebber K, Glötzl R. Highly sensitive fiber optic inclinometer: easy to transport and easy to install. 21st Int. Conf. Opt. Fibre Sensors, vol. 7753, 2011, p. 775352. doi:10.1117/12.884695.
- Wang YL, Shi B, Zhang TL, Zhu HH, Jie Q, Sun Q. Introduction to an FBG-based inclinometer and its application to landslide monitoring. J Civ Struct Heal Monit 2015;5:645–53. doi:10.1007/s13349-015-0129-4.
- Bang H-J, Kim H-I, Lee K-S. Measurement of strain and bending deflection of a wind turbine tower using arrayed FBG sensors. Int J Precis Eng Manuf 2012;13:2121–6. doi:10.1007/s12541-012-0281-2.
- Park Y, Elayaperumal S, Daniel B, Ryu SC, Shin M, Savall J, et al. Real-Time Estimation of 3-D Needle Shape and Deflection for MRI-Guided Interventions. IEEE/ASME Trans Mechatronics 2010;15:906–15.

 doi:10.1109/TMECH.2010.2080360.
- Roesthuis RJ, Kemp M, van den Dobbelsteen JJ, Misra S. Three-Dimensional Needle Shape Reconstruction
 Using an Array of Fiber Bragg Grating Sensors. IEEE/ASME Trans Mechatronics 2014;19:1115–26.
 doi:10.1109/TMECH.2013.2269836.
- O'Reilly OM. Kirchhoff's Rod Theory. Model. Nonlinear Probl. Mech. Strings Rods Role Balanc. Laws, Cham: Springer International Publishing; 2017, p. 187–268. doi:10.1007/978-3-319-50598-5 5.
- [29] Langer J, Singer D a. Lagrangian Aspects of the Kirchhoff Elastic Rod. SIAM Rev 1996;38:605–18.
 doi:10.1137/S0036144593253290.
- 344 [30] Askins CG, Miller GA, Friebele EJ. Bend and Twist Sensing in a Multiple-Core Optical Fiber. OFC/NFOEC 2008 2008 Conf. Opt. Fiber Commun. Fiber Opt. Eng. Conf., IEEE; 2008, p. 1–3. doi:10.1109/OFC.2008.4528404.
- Floris I, Calderón PA, Sales S, Adam JM. Effects of core position uncertainty on optical shape sensor accuracy.

 Meas J Int Meas Confed 2019;139. doi:10.1016/j.measurement.2019.03.031.
- Jäckle S, Strehlow J, Heldmann S. Shape Sensing with Fiber Bragg Grating Sensors. In: Handels H, Deserno TM, Maier A, Maier-Hein KH, Palm C, Tolxdorff T, editors. Bild. für die Medizin 2019, Wiesbaden: Springer Fachmedien Wiesbaden; 2019, p. 258–63. doi:10.1007/978-3-658-25326-4 58.
- 352 [33] Black RJ, Zare D, Oblea L, Park Y-L, Moslehi B, Neslen C. On the Gage Factor for Optical Fiber Grating Strain Gages. Proc Soc Adv Mater Process Eng 2008;52, 2008.
- Tosi D. Review and Analysis of Peak Tracking Techniques for Fiber Bragg Grating Sensors. Sensors 2017;17:2368. doi:10.3390/s17102368.
- Floris I, Sales S, Calderón PA, Adam JM. Measurement uncertainty of multicore optical fiber sensors used to sense curvature and bending direction. Meas J Int Meas Confed 2019;132.
 doi:10.1016/j.measurement.2018.09.033.
- Henken KR, Dankelman J, Van Den Dobbelsteen JJ, Cheng LK, Van Der Heiden MS. Error Analysis of FBG-Based Shape Sensors for Medical Needle Tracking. IEEE/ASME Trans Mechatronics 2014;19:1523–31. doi:10.1109/TMECH.2013.2287764.
- 362 [37] Wolfram S. The Mathematica Book, Fifth Edition. Wolfram Media, Inc; 2003. 363